


We excel in LOW COST and HIGH QUALITY SM-4115-PP (9872-00009)

MANY OTHER VARIATIONS AND OPTIONS ARE AVAILABLE



Gasket: As the nut is tightened on the thread, the gasket diameter will expand.

Recommended mounting hole size: 7/8" Recommended wall thickness: 1/32" to 3/8"

WIRING DIAGRAM Switch is closed when float is near stem Red wire L1 N.C.

SPECIFICATIONS

MATERIAL: Polypropylene **FITTING:** M16 threads with nut and sealing grommet **SWITCH:** SPST, 20 watt maximum

265 volts and 1 amp maximum values N.C. reversible to N.O.

WIRING: Red, 22 ga. PTFE, 24" length

MAXIMUM PRESSURE: 100 PSI

OPERATING TEMPERATURE: -20 °F to +180 °F



Do you need something to be different?

No problem, call or email and let us know how we can modify this product to meet your exact requirements.

RochesterSensors.com | 800-852-9984 | salesQT@rochestersensors.com

Since the suitability of these products depends upon a wide range of factors not in our control, Rochester Sensors expects and understands that you will conduct the testing and evaluation necessary to determine that these products are suitable for your application. Whilst every effort is made to ensure the above details are correct at the time of printing, Rochester Sensors reserves the right to make material changes, and or technical changes without notification. © *Rochester Sensors*. 11/23 *Rev* 1

